

September 19, 2007

Re: Shutting Down the SRX-Pro Server and the DVMS

Occasionally, the user may want to restart or shut the DVR down. Please remember that critical information may be missed, while the DVR isn't recording.

Closing down SRX-Pro Server without shutting down the DVR

In order to exit the SRX-Pro Server software and access the Windows Desktop, log into the SRX-Pro Server software as a master user (i3dvr) and simultaneously press **Ctrl + Alt + Shift + F4** on your keyboard. Re-type the password in the Confirm Password window. The SRX-Pro Server software will be closed.

Shutting down the DVR. Windows XPe

Follow the instructions below to shut down a DVR that runs on Embedded Windows OS (XPe): Lite and Ultra Lite units only.

A. Shutting Down with SRX-Pro Server software running

(Also applies to Windows Professional or Home)

Go **File** -> **Shutdown** menu. Wait while DVR is shutting down.



B. Shutting Down with SRX-Pro Server software closed.

(Also applies to Windows Professional or Home)

i3dvr users: By first logging off the current user account and then shutting down Windows OS.

1. Press **Ctrl + Alt + Scroll Lock** key combination on your keyboard.
2. In the *Windows Security* window, click **Log Off**.
3. In the *Log Off Windows* confirmation window, click **Log Off** again. Wait while Windows logs off the active user account.
4. In the *Log On to Windows* window, click **Shut Down...**
5. In the *Shut Down Windows* window, click **OK**. Wait while DVR is shutting down.

Administrator users: By clicking **Start** -> **Shut Down**

Shutting down the DVR. Windows Professional or Home editions

- A. Shutting down with SRX-Pro Server running.**
same as for Windows XPe
- B. Shutting Down with SRX-Pro Server software closed.**
same as for Windows XPe
- C. Shutting Down with SRX-Pro Server software closed**
 1. Click **Start** button
 2. Click **Run...**
 3. To restart, type "shutdown -r -t 00", and click **OK**.
 4. To power off, type "shutdown -s -t 00", and click **OK**.

Cold Reboot/Shutdown

If the system is frozen, you may need to perform a cold reboot.

Rackmount units and newer Compact Wallmount units:

Press and hold the power button for several seconds until the unit shuts down.

Older Compact Wallmount units:

Take a sharp object and depress the pin hole located on the front plate of the DVR; hold it for several seconds until the unit shuts down.

With any questions, please contact our technical support at 1.877.877.7241 or support@i3dvr.com

Thank you very much for your attention and cooperation.
Best regards,



Olga Alexeenko
Training Coordinator
1.416.261.2266 x135
oalexeenko@i3dvr.com